www.stephill-generators.co.uk
+44 (0) 1933 677911

3400HM4S

3.4kVA Petrol Generator

GENERATOR SPECIFICATION	
Voltage	230/115
Phase	1
Frequency	50Hz
Prime Power (PRP)	3.4 kVA / 2.7 kW
Alternator	NSM K100D
Alternator Type	Brushless - Smooth Waveform
Fuel tank capacity	3.1 Litres
Autonomy 75% load	2.5 Hours
LWA	96
dBA @ 7M	71

ENGINE SPECIFICATION	
Engine	Honda GX200
Emissions certified	EU Stage V
Cylinders	Single
Distribution	O.H.V.
Aspiration	Naturally aspirated
Cooling	Air
Displacement	196 cm³
Rpm	3000
Starting system	Recoil
Fuel	Unleaded 86 octane or higher



DIMENSIONS (mm)			WEIGHT (KG)
Length	**Width**	**Height**	42
610	420	415	

GX Engine 3 YEAR WARRANTY

HONDA
The Power of Dreams

CONTROL BOX

- 115V: 1 x 16A & 1 x 32A BS4343 sockets.
- 230V: 2 x 16A BS4343 sockets.
- Reset circuit breaker overload protection.
- Voltage selector switch.

STANDARD FEATURES

- Oil alert/low oil shutdown.
- 3 Year engine warranty (Limited).
- Full wrap-around frame.
- Brushless smooth waveform alternator.

OPTIONS

- AVR (Automatic Voltage Regulator).
- Single voltage.
- Long run tank.
- Trolley kit.*

* Different model used to illustrate trolley option.



POWER DEFINITION

Prime Power (PRP) : Applicable for supplying power to varying electrical load for unlimited hours in accordance ISO 8528-1 under the agreed operating conditions with the maintenance intervals and procedures being carried out as prescribed by the manufacturers.